




- » Small size and lightweight design
- » 36 hours operation time, 60 hours stand-by time \*
- » A single unit with internal GSM and GPS antennas
- » Programmable buttons
- » Make/receive voice calls
- » 50 channel GPS receiver and assisted GPS feature
- » Firmware over the air (FOTA)

\* The battery life varies depending on the frequency of sending the data requested from the device.

## TECHNICAL SPECIFICATIONS

<b>Model</b>	Treyki
<b>Producer</b>	Arvento Mobile Systems
<b>Operating Temperature</b>	0°C to +60°C *
<b>Dimensions</b>	66 mm x 38 mm x 19 mm
<b>Weight</b>	55 gr
<b>Data Storage</b>	64 Mb
<b>Battery Type</b>	Li-ion 900 mAh
<b>GSM Modem</b>	Quad-Band GSM/GPRS 850-900-1800-1900 MHz <b>Output Power</b> • Class 4 (2W) @ 850/900 MHz • Class 1 (1W) @ 1800/1900 MHz <b>Sensitivity</b> • -108 dBm @ 850/900 MHz • -107 dBm @ 1800/1900 MHz <b>GPRS</b> • GPRS Class 10 • Mobile Station Class B • Coding Scheme 1 to 4 • PBCCH Support • SMS Support Superior echo cancellation & noise reduction

<b>GSM Antenna</b>	Internal
<b>GPS Receiver</b>	50 Channel GPS L1 Frequency, C/A Code SBAS: WAAS, EGNOS, MSAS Sensitivity: -162 dBm AGPS Support Accuracy: GPS 2,5 m, GPS+SBAS 2.0 m
<b>Sensors</b>	G-Sensor (for motion)
<b>Buttons</b>	"YES", "NO", "S.O.S.", "1", "2"
<b>Connector</b>	Mini USB (B) (Charging)
<b>LED Indicators</b>	Battery, GSM and GPS
<b>Firmware Over the Air</b>	Present
<b>Certificates</b>	SAR 

\* The battery life varies depending on the frequency of sending the data requested from the device.

